

IN THE CLAIMS

Please amend the claims as follows:

1. (original) A method of correlating a sampled direct sequence spread spectrum signal with a locally provided replica signal containing a spreading code comprising the steps of:

- combining the bit or bits of at least two signal samples of the received signal to form a first word;
- providing a second word containing bits corresponding to the replica signal; and
- executing one or more software based instructions to process the first and second words in order to obtain a correlation value.

2. (original) A method according to claim 1 wherein the processing of the first and second words is done using hardwired circuitry.

3. (original) A method according to claim 1 wherein the processing of the first and second words includes a word based XOR operation or its inverse and a summation of the results of that operation.

4. (original) A method according to claim 1 wherein a software based instruction is executed to form the first word.

5. (original) A method according to claim 1 wherein each sample of the spread spectrum signal contains at least one magnitude bit and a sign bit; wherein the first word is formed by combining the magnitude bit or bits of at least two signal samples; wherein a third word is formed by combining the sign bit of at least two signal samples; and wherein one or more software based instructions are executed to process the first, second and third words in order to obtain a correlation value.

6. (original) A signal processor configured for correlating a sampled direct sequence spread spectrum signal with a locally provided replica signal containing a spreading code by combining the bit or bits of at least two signal samples of the received signal to form a first word, providing a second word containing bits corresponding to the replica signal, and executing one or more software based instructions to process the first and second words in order to obtain a correlation value.

7. (original) A signal processor according to claim 6 wherein the processing of the first and second words is done using hardwired circuitry.

8. (original) A signal processor according to claim 6 wherein the processing of the first and second words includes a word based XOR operation or its inverse and a summation of the results of that operation.

9. (original) A signal processor according to claim 6 wherein a software based instruction is executed to form the first word.

10. (original) A signal processor according to claim 6 wherein each sample of the spread spectrum signal contains at least one magnitude bit and a sign bit; wherein the first word is formed by combining the magnitude bit or bits of at least two signal samples; wherein a third word is formed by combining the sign bit of at least two signal samples; and wherein one or more software based instructions are executed to process the first, second and third words in order to obtain a correlation value.

11. (currently amended) A direct sequence spread spectrum signal receiver comprising an antenna and an RF front-end including an

analogue to digital converter for receiving spread spectrum signals and outputting corresponding signal samples; and a signal processor according to ~~any of claims 6 to 10~~claim 6.

12. (currently amended) A computer-readable storage medium having recorded thereon data containing instructions for performing a method according to ~~any of claims 1 to 5~~claim 1.

13. (currently amended) A computer program comprising instructions for performing a method according to ~~any of claims 1 to 5~~claim 1.